



**HESTORE.HU**

elektronikai alkatrész áruház

**EN:** This Datasheet is presented by the manufacturer.

Please visit our website for pricing and availability at [www.hestore.hu](http://www.hestore.hu).

# Digital Storage Oscilloscope

1GSa/s, 200MHz, 1M Record Length

## DSO5000B Series

### Feature

- 200/100/60MHz Bandwidth; 1GSa/s Sample Rate;
- 2 Channel Oscilloscope; 1M Record Length;
- 7 inch 64K color LCD display, Resolution 800x480;
- 32 kinds of Automotive measurement, with FFT function;
- Powerful trigger function: Video, Edge, Pluse Width, Slope, Overtime, Alternate Trigger.

### Specification

Model	DSO5202B	DSO5102B	DSO5062B	
<b>Horizontal</b>	Bandwidth	200MHz	100MHz	60MHz
	Sampling Rate Range		1GSa/s	
	Equivalent Sample Rate		25GSa/s	
	Memory Depth (Sample Points)		1M	
	SEC/DIV Range	2ns/div~40s/div	4ns/div-80s/div	
	Delay Time Accuracy	±50ppm in any ≥1ms time intervals		
	Delta Time Measurement Accuracy (full bandwidth)	Single-shot, "sampling" mode, ± (1 sampling interval + 100ppm × readings + 0.6ns) > 16 times above average, ± (1 sampling interval + 100ppm × readings + 0.4ns) Sampling interval = SEC/DIV÷200		
<b>Vertical</b>	A/D Converter	8-bit resolution, each channel sampled simultaneously		
	VOLTS/DIV Range	2mV/div~5V/div at input BNC		
	Position Range	±50V(5V/div); ±40V(2V/div~500mV/div); ±2V(200mV/div~50mV/div); ±400mV(20mV/div~2mV/div)		
	Rise Time at BNC	1.7ns	3.5ns	5.8ns
	DC Gain Accuracy	±4% for Sample or Average acquisition mode, 5mV/div to 2mV/div ±3% for Sample or Average acquisition mode, 5V/div to 10mV/div		
<b>Trigger</b>	Trigger Sensitivity(Edge Trigger Type)	DC(Intelnal): 1div from DC to 10MHz, 1.5div from 10MHz to 100MHz, 2div from 100MHz to 200MHz; DC(EXT): 200mV from DC to 100MHz, 350mV from 100MHz to 200MHz; DC(EXT/5): 1V from DC to 100MHz, 1.75V from 100MHz to 200MHz; AC: Attenuates signals below 10Hz; HF Reject: Attenuates signals when above 80KHz; LF Reject: The same as DC coupling limit when frequency above 150KHz; Attenuates signals when below 150KHz.		
	Trigger Level Range	CH1, CH2: ±8 divisions from center of screen; EXT: ±1.2V; EXT/5: ±6V		
	Typical accuracy for signals having rise and fall time ≥ 20ns)	CH1, CH2:±(0.2div × V/div) (within ±4 divisions from center of screen); EXT: ±(6% of setting+40mV); EXT/5: ±(6% of setting+200mV)		
	Holdoff Range	100ns - 10s		
	Set Trigger Level to 50% (typical)	For the input signals ≥ 50Hz		
	Trigger Type	Video, Edge, Pluse Width, Slope, Overtime, Alternate Trigger.		
	Normal, Peak Detect	Upon single acquisition on all channels simultaneously		
<b>Acquisition</b>	Average	After N acquisitions on all channels simultaneously, N can be set to 4, 8, 16, 32, 64 or 128		
	Input Coupling	DC, AC or GND		
<b>Input</b>	Input Impedance, DC coupled	1MΩ±2% for 20pF±3 pF		
	Probe Attenuation	1X, 10X,		
	Supported Probe Attenuation Factor	1X, 10X,100X, 1000X		
<b>Measurement</b>	Max. Input Voltage	CAT I and CAT II: Installation type: 300VRMS(10×); CAT III: 150VRMS(1×)		
	Cursors	The difference between voltage cursors ΔV; The difference between time cursors ΔT; Reciprocal of ΔT in Hertz (1/ΔT).		
	Automatic	Frequency, Period, Mean, Pk-Pk, Cycli RMS, Minimum, Maximum, Rise time, Fall Time, +Pulse Width, -Pulse Width, Delay1-2Rise, Delay1-2Fall, +Duty, -Duty, Vbase, Vtop, Vmid, Vamp, Overshoot, Preshoot, Preiod Mean, Preiod RMS, FOVShoot, RPRESHoot, BWIDTH, FRF, FFR, LRR, LRF, LFR, LFF		
	Display	7 inch 64K color LCD; 800x480 pixels; Adjustable (16 gears) with the progress bar		
<b>Other</b>	Voltage	100-120VACRMS(±10%),45Hz to 440Hz. CAT II ; 120-240VACRMS(±10%),45Hz to 66Hz. CAT II		
	Power	< 30W		
	Fuse	2A, T rating, 250V		
Size & Weight	313mm(L)x108mm(W)x142mm(H); 2.08KG(without Packing)			