EN: This Datasheet/Document is presented by the manufacturer.

Please visit our website for pricing and availability at www.hestore.hu.

PRODUCT DATASHEET

NiMH Battery Charger (CHFC3)

Universal Charger



MAXIMIZES PERFORMANCE

- Helps batteries retain capacity by preventing damage from overcharge

ENSURES FULL CHARGE


- Charges batteries to 100% capacity

EASY TO USE

- LED lights indicate when batteries are charging

VERSATILE

- Charges AA, AA, C, D and 9V NiMH batteries



Before Using Your Charger:
Please read all instructions and cautionary markings on the battery charger, batteries, and device.

Best used with *Energizer*® NiMH batteries.

EMEA Region

Download Instructions (multilingual)

Product Detail:

Designation: Universal Charger
Model: CHFC3
Color: Black
Charging Capability: AA/AAA/C/D/9V

Charging Times: (estimated)

Battery (NiMH)	Capacity (mAh)	Estimated (time)
AA	1300-2000	3-4 hrs
AA	2000-2300	4-5 hrs
AAA	500-800	2-3 hrs
C/D	2500	5 hrs
9V	175	8 hrs

Shutoff Mechanism: Delta V Detection: 5mV per cell for "AA-AAA-C-D"
Timer Control: 2 or 4 "AA-C-D": 5 hrs
2 or 4 "AAA": 3.5 hrs
1 or 2 "9V": 8 hrs

Charging Current: "AA-C-D" 650mA
"AAA" 400mA
"9V" 30mA

Trickle Charge: None
Input Rating: 100-240VAC, 50/60Hz, 6W
Typical Weight 322 grams
Dimensions (mm): 48 x 199 x 107 (H x L x W)
Safety Features: Short Circuit and Reverse Polarity Protection
Primary Battery Detection
Bad Battery Detection
Delta V Charging Cut Off
Safety Timer to Prevent Overcharge

Important Notice
This datasheet contains information specific to products manufactured at the time of its publication.
©2017 Energizer Brands, LLC
Contents herein do not constitute a warranty.