


EN: This Datasheet is presented by the manufacturer.

Please visit our website for pricing and availability at www.hestore.hu.

D08-RGB colorful sound-sensitive VU meter



Features:

- -Built-in highly sensitive microphone
- -32pcs WS2812 LED
- -Different display modes
- -Adjustable modes
- -Adjustable brightness
- -Adjustable speed
- -AGC (automatic gain control)
- -Intelligent noise reduction
- -Built-in accumulator
- -Bluetooth connection and mobil application control, multiple devices at once

Parameters:

-Model: D08-RGB -Input voltage: 5V DC

-Input connector: TYPE-C USB -Frequency response: 100...16kHz

-Dimensions(L x W x H): 18.5 x 16 x 182mm

-Weight: 60g

Wavelength:

-Red: 620...625nm -Green: 520...525nm -Blue: 460...470nm

Download application:



Button functions:

POWER: Long press to power on or power off

Short press to show accumulator level:

4 Green: 75...100% 3 Green: 50...75% 2 Green: 25...50% 1 Green: <25% 1 Red: <5%

1 Red flashes before automatically power off

MODE/SPEED: Short press to change mode

Long press to change the next speed level: 1-5

COLOR/BRIGHT: Short press to change color mode

Long press to change the next brightness level: 1-4

Notice: Don't connect the power input OVER 5V, otherwise the board demaged!

Don't immerse in water!

Don' use under the condition of humidity higher than 90%!

Don't use any solvent of liquids to wipe the screen except absolute alcohol!

Don't disassemble by yourself!

Don't use for children younger than 6 years old!